

VARIABLE FREQUENCY PWM CONTROLLER CIRCUIT

FIELD OF THE INVENTION

[0001] The present invention relates to switching mode power supplies, and more specifically to a varied frequency pulse width modulation controller for low standby loss solution.

BACKGROUND OF THE INVENTION

[0002] The trend in the design of switching mode power supplies has been toward relatively low power loss, low ripple and low noise under light load condition, especially for those widely used adaptors for notebooks, computers, and chargers for mobile telecommunication apparatus. This kind of power supplies frequently operates under a light or zero load condition, which is named as the standby operation mode.

[0003] A flyback converter is the most commonly used topology for this application with pulse width modulation (PWM) control for the output regulation. To achieve relatively very low power loss under light or open load condition, it is the key factor to control the power stage to operate at a relatively very low switching frequency to decrease the switching loss and driving loss of the generally used MOSFET power switch. Meanwhile, the control circuit dissipates relatively low loss due to relatively low frequency operation.

[0004] The conventional PWM controller circuit according to the general prior art always operates at a constant frequency, corresponding to the switching period T as shown in FIG. 1, which shows the operating PWM signal for the normal and standby operation mode respectively. The power circuit operates with relatively a long on time PWM, $T_{on,nor}$, and thus a high

duty cycle under normal load condition. In the standby operation mode, the power circuit always operates with relatively a very short time $T_{on,sb}$ and thus a very small duty cycle, but the switching frequency is still high as normal operation, resulting in relatively much switching loss and driving loss of the main switch and much power loss of the controller which are the major parts of the standby loss. Therefore, the standby loss of the converter will be relatively high. However the advantage of the PWM controller circuit is that the output ripple and noise are relatively very low even at the standby operation mode.

[0005] Moreover, there are generally two methods to decrease the switching related loss which is the main component of the standby loss. One is to decrease the switching frequency by regulating the T_{off} time of the PWM signal while keeping a constant T_{on} time of the PWM signal for standby operation. Please refer to FIG. 2. In the standby operation mode, the constant switching on time of PWM signal is $T_{on,sb}$, which is equal to the counterpart $T_{on,nor}$ for the normal operation mode. But the T_{off} time is regulated as $T_{off,sb}$, which is relatively much longer than that $T_{off,nor}$ for the normal operation mode. As a result, the switching period is relatively much longer than that of the normal operation mode and the switching frequency is relatively much lower which benefits to the relatively low standby loss in the standby operation mode as mentioned before.

[0006] One drawback of this control method is that the conversion power at each switching cycle will be relatively high due to the constant on time of the PWM signal in the standby operation mode. Therefore, relatively high output voltage noise and even audible noise might be

introduced to the converter though the standby loss can be effectively reduced.

[0007] The other method is a burst mode control for the standby operation mode. Please refer to FIG. 3 for the operation PWM signal with this control mode. In the normal operation mode, the PWM signal is relatively with a high frequency and long on time as $T_{on,nor}$. In the standby operation mode, the on time of PWM signal can be regulated relatively short as $T_{on,sb}$ at each switching period, but after several continuous switching periods, some switching periods will be skipped. Therefore, in the standby operation mode, the equivalent switching period will be T_{sb}/n , where n is the numbers of PWM pulses during the T_{sb} time. It can be seen that, in the standby operation mode, the equivalent switching period of the PWM signal is longer than that of the normal operation mode. So, the switching related loss can be effectively reduced and thus the relatively low standby loss can be achieved.

[0008] But there are problems with this control mode also. In the standby operation mode, the conversion power of the converter during the several continuous switching periods with PWM pulses will be relatively high, resulting in relatively high output voltage noise. Meanwhile, the several continuous switching periods with PWM pulses occur during a relatively long T_{sb} period corresponding to a relatively low frequency. This will also introduces the audible noise to the converter.

[0009] It is therefore attempted by the applicant to deal with the above situation encountered with the prior art.

SUMMARY OF THE INVENTION

[0010] A new PWM signal generating scheme is presented, as shown in FIG. 4. The on time and the off time of the PWM signal are regulated simultaneously according to the scheme. Each of the generated PWM signals will have relatively a very short on time and a very low frequency in the standby operation mode, and have relatively a high frequency and a long on time in the normal operation mode, thus the aforementioned ripple and noise can be eliminated while the relatively low standby loss feature is maintained.

[0011] In more details, each of the PWM signals will have relatively a long on time $T_{on,nor}$ and a short switching period T_{nor} in the normal operation mode according to the present invention. Thus, the duty cycle D_{nor} , which is equal to $T_{on,nor}/T_{nor}$, is relatively high and the switching frequency f_{nor} , which is equal to $1/T_{nor}$, is relatively high too. These relatively high duty cycle and high switching frequency are advantageous to the relatively high power density and high efficiency design of the power converter.

[0012] As the load decreasing, the on time of the PWM signal is decreased while the off time of the PWM signal is increased. As a result, the on time $T_{on,sb}$ of the PWM signal is reduced to a relatively low value, the off time $T_{off,sb}$ and thus the switching period T_{sb} are increased to a relatively high value in the standby operation mode. Therefore, relatively very low duty cycle and very low switching frequency can be achieved in the standby operation mode of the power converter, wherein relatively low standby loss, low output voltage noise and no audible noise are realized simultaneously.

[0013] In accordance with the preferred embodiment of the present invention, a circuit generating a wide range of variable frequency (VF) PWM control signals is provided. An error-amplified voltage $V_{E/A}$ is generated by a feedback loop. And then this $V_{E/A}$ is input into a ramp generator. The ramp generator is composed of a controllable charge current source, a controllable discharge current source, and a timing capacitor. These two current sources charge and discharge the timing capacitor, which generates a ramp signal. Typically, a PWM comparator, and a hysteretic voltage comparator will be employed to process this ramp signal and generate a PWM signal.

[0014] The controllable charge current source and controllable discharge current source are controlled by the value of the error-amplified voltage $V_{E/A}$. Corresponding to the load decreasing condition, the lower the error-amplified voltage $V_{E/A}$ is, the higher the charge current and the lower the discharge current will be. Relatively, the rising time of the ramp signal will be shorter, and the descending time will be longer. Therefore, the generated PWM signal features relatively a lower duty cycle and a lower frequency.

[0015] The present invention allows relatively a low duty cycle and a low frequency operation, which makes a power converter operate with relatively low ripple, low noise and low standby loss. This is a significant improvement over the prior art.

[0016] The present invention may best be understood through the following description with reference to the accompanying drawings, in which:

BRIEF DESCRIPTION OF THE DRAWINGS

[0017] FIG. 1 shows a PWM signal generating scheme of a conventional PWM controller;

[0018] FIG. 2 shows a frequency decreasing PWM signal generating scheme for low standby loss;

[0019] FIG. 3 shows a burst mode PWM signal generating scheme for low standby loss;

[0020] FIG. 4 shows a PWM signal generating scheme for low standby loss according to the present invention;

[0021] FIG. 5 shows a preferred embodiment of the controller circuit according to the present invention;

[0022] FIG. 6 shows the operation waveforms of the controller circuit according to the first preferred embodiment of the present invention;

[0023] FIG. 7 shows another preferred embodiment of the controller circuit according to the present invention; and

[0024] FIG. 8 shows the operation waveforms of the controller circuit according to the second preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

[0025] Although this invention is susceptible to embodiments of many different forms, a preferred embodiment will be described and illustrated in detail herein. The present disclosure exemplifies the principle of the invention and is not being considered a limitation to the broader aspects of the invention to the particular embodiment as described.

[0026] In FIG. 5, a circuit diagram to realize the VF PWM control scheme according to the present invention is shown. The overall circuit of

the invention has three parts including a feedback loop, a synchronous signal generator and a PWM comparator.

[0027] The output voltage is input to the feedback loop which in-turn outputs an error-amplified voltage $V_{E/A}$. The $V_{E/A}$ signal is firstly input to a synchronous signal generator, which includes a VCO (Voltage Control Oscillator) and selectively includes a pulse generator, which is an optional component coupled to the VCO and can be omitted without damping the functions of the synchronous generator, and outputs a variable frequency synchronous signal according to the value of the $V_{E/A}$ signal. The PWM comparator, including a comparator AP and a RS flip flop, with the synchronous signal, the $V_{E/A}$ signal and a ramp signal as inputs and generates a PWM signal.

[0028] The operation waveforms can be illustrated in FIG. 6a and FIG. 6b, wherein FIG. 6a shows the standby operation mode and FIG. 6b shows the normal operation mode. In the standby operation mode, the $V_{E/A}$ signal has relatively low value. As a result, the VCO of the synchronous signal generator produces a relatively low frequency oscillating waveform to the pulse generator according to the value of the $V_{E/A}$ signal. Then, the pulse generator outputs a pulse with this relatively low frequency, $1/T_{sb}$, to the PWM comparator as the synchronous signal. In more details, the synchronous signal is coupled to the S terminal of the RS flip-flop. Meanwhile, the $V_{E/A}$ signal is coupled to one input of the comparator AP of the PWM comparator and a ramp signal is coupled to another input of the comparator AP. Hereby, the ramp signal can be a current signal of the main switch of the power converter. Once the synchronous signal triggers the RS flip-flop, the PWM signal begins its high level till the voltage of the

ramp signal rises to equal with the voltage of $V_{E/A}$ signal. This time duration, shown as $T_{on,sb}$ which is the on time of the PWM signal, is relatively very low because of the relatively low voltage of the $V_{E/A}$ signal in the standby operation mode. Therefore, the output PWM signal will have a relatively short on time $T_{on,sb}$ and a relatively low frequency.

[0029] As to the normal operation mode with the operations waveforms shown in FIG. 6b, the voltage of the $V_{E/A}$ signal is relatively high. With the same scheme as aforementioned in the standby operation mode, the generated synchronous signal will have relatively a high frequency corresponding to a low period as T_{nor} . While the PWM signal will have a relatively long on time shown as $T_{on,nor}$. Thus the PWM signal features relatively the high frequency and high duty cycle at normal operation mode.

[0030] In FIG. 7, another controller circuit according to the present invention is shown, in which the off time and the on time of the generated PWM signal are changed with the error-amplified voltage simultaneously. A PWM signal with relatively a very low duty cycle and a low frequency can be generated by this means.

[0031] The overall circuit of this invention comprises three parts: a feedback loop, which inputs with an output voltage V_o of a switching mode power converter (not shown) and outputs an error-amplified voltage $V_{E/A}$, a ramp generator, and a PWM comparator.

[0032] The ramp generator is formed with a charge current source I_c , a discharge current source I_d , and a timing capacitor C_T .

[0033] Two comparators, shown in FIG. 7 as A1 and A2, and a RS flip-flop make up the PWM comparator. V_H and V_L , as a high reference voltage and a low reference voltage respectively, are connected to a

noninverting terminal of the comparator A1 and an inverting terminal of the comparator A2 respectively.

[0034] The output voltage V_o of the switching mode power converter is input into the feedback loop. An error-amplified voltage is generated by the feedback loop as $V_{E/A}$. As the conventional design of the feedback loop, when the output load is high, $V_{E/A}$ will be high relatively. The $V_{E/A}$ voltage controls the charge current source I_c and the discharge current source I_d . The voltage of the $V_{E/A}$ controls the values of I_c and I_d . The output PWM signal, which is an optional input of the ramp generator, can be selectively omitted without damping the functions of the ramp generator. When $V_{E/A}$ is high, the value of I_c of the ramp generator will be high and the value of its I_d will be low relatively.

[0035] The operation waveforms can be illustrated in FIG. 8a and FIG. 8b, wherein FIG. 8a shows the standby operation mode and FIG. 8b shows the normal operation mode. It can be seen from the aforementioned analysis, the charge current I_c will be high in the standby operation mode due to the relatively low $V_{E/A}$. Thus, the T_{on} time of the PWM signal, which is the time of the charge current I_c charging the voltage across CT from V_L to V_H , will be relatively short. Meanwhile, the discharge current I_d is relatively low and the T_{off} time of the PWM signal, which is the time of the discharge current I_d discharging the voltage across CT from V_H to V_L , will be relatively long. Please refer to FIG. 8b. With the same principle, when the converter operates under a normal load condition, the T_{on} time of the PWM signal will be relatively long while T_{off} time is relatively short.

[0036] As a result, this PWM controller features with relatively a high switching frequency and a high duty cycle under the normal load operation,

and a low switching frequency and a low duty cycle under the light load operation with this second embodiment of the present invention.

[0037] Therefore, with the PWM control of the present invention, the switching mode converter can be designed with relatively high frequency, which benefits to high power density. At light load, the converter will be operated in relatively a low switching frequency and a low duty cycle, therefore, a relatively low standby loss with low output ripple. For low control circuit loss at standby mode operation, the charging and discharging of I_c and I_d can be modulated by output PWM signal. When the PWM signal is in a high voltage level, the I_c is set to the value as aforementioned while the value of I_d is set to zero. When the PWM signal is in a low voltage level, the I_d is set to the value as aforementioned while the value of I_c is set to zero.

[0038] Although the present invention has been described in terms of the presently preferred embodiment, it is to be understood that such disclosure is not to be interpreted as limiting. Various alterations and modifications will no doubt become apparent to those skilled in the art after having read the above disclosure.